



รายละเอียดสินค้า อุปกรณ์เสริมสำหรับไม้กั้นประตู้เข้า-ออก





Wiegand-02

Features:

- Support offline work, TCP/IP communication;
 allow direct connection with computer via network
 cable. Support LAN, remote control by PC software.
- Compared to standard standalone access controller, this device separates the reader and the controller to individual parts so to realize higher safety request of your customer.
- This device is compatible with all RF reader which is with any type of Wiegand standard communication format available in the market.
- Wrong connection of reader or data cable will not destroy the device or unlock the door illegally.
- Effect inhibition of static electricity and surge from input and feedback interference from electronic locks.
- All-in-one-card management system: normal shift and multi-shifts time attendance management system; fixed ration dining management system; meeting attendance management system; online patrol management system and security alarm management system.

Model

Communication

English Software supportable database Function Description

Door

Card Reader

Card User q'ty allowed

Event buffer

Reader Input Format

Delay time for unlocking

Max q'ty of controller

Power interruption protection measure

Max Distance from Reader to Controller

Max Distance between Controllers
Fire and alarm linkage

Compulsive open and close door at long time

Open door in remote distance Anti pass back and tail

Inter block

Multi-card open door

Open long time at specified time

Urgency locking

First card unlocking

Keypad (card + password, supper password)

Electronic map

Power supply Color of case

PCB Size

Case Size

Operation Temperature

Operation Humidity

DC02-TCP / Wiegand-02

TCP/IP 10M/100M adaptive

Access and SQL

Control two doors, enter via card swiping and exit via card swiping or button.

2

4

20,000

100,000

Wiegand 26 (compatible with all readers under the agreement, such as Motorola, HID, EM,

Mifare one, etc.).

1-600 seconds(adjustable)

No limit

High Speed Memory, Records never lose

100m (suggestion distance 80m)

Depends on net coverage area

If no connection with the expansion board,

only has software interface alarm, and drive

the computer speaker.

Security alarm.

If connected with expansion board, is able to alarm by hardware, if connected with

strengthened expansion board, then is able to

YES

YES

YES

YES

YES

YES

...

....

YES

ILO

YES

YES

ILO

12VDC 4-7A

Brown box

160mm*106mm

273mm*228mm*65mm

-40C-70C

10-90 % RH, No Condensation